Honeywell



Model 3161

Tension/Compression In-Line Load Cell

DESCRIPTION

The small-diameter, cost-efficient, fatigue-resistant load cells are designed to be used in applications that require an ability to mount in an existing system with restricted working area. They are commonly used in fluid power transfer systems. Their low cost and ease of mounting allow simultaneous testing of multi-element systems.

They may be directly attached to the piston rod of a hydraulic cylinder. Side-mounted cable connectors allow cable assemblies to be supported without affecting movement of the cell during tension or compression loading.

FEATURES

- 2000 lb to 25000 lb range
- 0.15 % linearity
- 0.1 % hysteresis
- Fatigue resistant
- Adapts directly to hydraulic cylinder
- Small diameter allows mounting in restricted areas
- Low deflection

Model 3161

PERFORMANCE SPECIFICATIONS

Characteristic	Measure
Load range ¹	2000, 5000, 10000, 25000 lb
Non-linearity	±0.15 % of rated output
Hysteresis	±0.1 % of rated output
Repeatability	±0.05 % of rated output
Output @ rated capacity	±2 mV/V (nominal)
Operation	Tension/compression
Resolution	Infinite
Standard calibration	Tension (+) and compression (-)

ENVIRONMENTAL SPECIFICATIONS

Characteristic	Measure		
Temperature, operating	-54 °C to 93 °C [-65 °F to 200 °F]		
Temperature, compensated	21 °C to 77 °C [70 °F to 170 °F]		
Temperature effect, zero	±0.002 % of rated output/°F		
Temperature effect, output	±0.002 % of reading/°F		

ELECTRICAL SPECIFICATIONS

Characteristic	Measure			
Strain gage type	Foil			
Excitation (maximum)	20 Vdc or Vac RMS			
Insulation resistance	> 5000 mOhm @ 50 Vdc			
Bridge resistance (tolerance)	350 ohm			
Number of bridges	1 or 2			
Zero balance	±1.0 %			


MECHANICAL SPECIFICATIONS

Characteristic	Measure		
Static overload capacity	150 % of nominal capacity		
Material	Carbon steel		
Natural frequency	See table		

RANGE CODES

Range Code	Available ranges		
DL	2000 lb		
DR	5000 lb		
DV	10000 lb		
EM	25000 lb		

TYPICAL SYSTEM DIAGRAM



Mating Connectors & Cables

023-LW181-023-LF Mating Connector

7205-76-XX* Mating connector & 6 conductor cable

(unamplified unit with sense leads but not shunt cal)

7205-75-XX** Mating connector & 4 conductor cable

(unamplified unit without sense leads but not shunt cal)

7205-83-XX* Mating connector & 6 conductor cable (for connection to instrument 7541)

7205-82-XX** Mating connector & 4 conductor cable (for connection to instrument 7541)

* XX represents length in feet 100ft maximum

** XX represents length in feet 20ft maximum


Tension/Compression In-Line Load Cell


NATURAL FREQUENCY

Nominal load limit capacity F _z				Static extraneous load limits				
lb	N	Static overload capacity (% of nominal capacity)	Fatigue capacity (% of nominal capacity)	Shear F _x or F _y (lb)	Bending M _x or M _y (lb-in)	Torque M _z (lb-in)	Deflection at nominal load limit (in)	Ringing frequency (Hz)
2K	10K	150	100	850	3800	3500	0.003	5000
5K	20K	150	100	850	3800	3500	0.003	6200
10K	50K	150	100	850	3800	3500	0.003	7100
25K	125K	150	100	2040	6750	9600	0.003	11000

MOUNTING DIMENSIONS

Model	A cm [in]	B cm [in]	C cm [in]	D cm [in]	E cm [in]	F cm [in]	G cm [in]	H cm [in]
3161	17,48 [6.88]	2,54 [1.0]	11,28 [4.44]	4,29 [1.69]	6,05 [2.38]	1,27 [0.50]	4,14 [1.63]	0,64 [0.25]





Model 3161

NOTES

1. This unit calibrated to Imperial (non-Metric) units.


Tension/Compression In-Line Load Cell

Warranty. Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Honeywell's standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items it finds defective. The foregoing is buyer's sole remedy and is in lieu of all warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.

While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.


Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

For more information about Sensing and Control products, visit www.honeywell.com/sensing or call +1-815-235-6847 Email inquiries to info.sc@honeywell.com



• DO NOT USE these products as safety or emergency stop devices or in any other application where failure of the product could result in personal injury.

Failure to comply with these instructions could result in death or serious injury.



- The information presented in this catalogue is for reference only. DO NOT USE this document as product installation information.
- Complete installation, operation and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in death or serious injury.

Sensing and Control
Automation and Control Solutions
Honeywell
1985 Douglas Drive North
Golden Valley, MN 55422 USA
+1-815-235-6847

Honeywell